

ATARI Reference

Computer Equipment

- Atari 800/800XL/1200XL/130XE with 64K and the Atari 400 with 48K.
- One disk drive required, 2 disk drives recommended.
- Dot matrix printer selected from the list on this sheet.

Booting Your System

- Insert Atari AwardWare program disk in Drive 1. If two drive system, insert graphics disk in Drive 2.
- Turn monitor, printer, and disk drive(s) ON.
- While holding down your "Option" key (except on the 400 and 800 models) turn ON computer until the screen turns blue.
- AwardWare self boots.

Important Keys



RETURN KEY: Makes a selection.



CURSOR MOVEMENT KEYS:

Moves cursor up and down to highlight choices. Use with Control key to move up and down in the text mode.



Moves cursor right and left to highlight choices. Use with Control key to move left and right in the text mode.




EDITING KEYS: This key deletes the last character typed.



By pressing these keys at the same time you delete the character the cursor is currently on.



ESCAPE KEY: Returns you back to the previous menu. Also exits the text mode.



OPTION KEY: See "Booting Your Computer" for instructions on how to use this key.



By pressing SHIFT and number 3 keys at the same time you will be able to stop the printing process ONLY at the D(draft) or F(final) prompt.

Printer Setup

If Your Printer is a:	Make This Choice From Printer Setup Menu
Okidata M 1292 (Microline P.M.)	Oki 29X (Microline)
Radio Shack DMP 500	DMP 500 Tandy
Epson LQ 800**	LQ 800 Epson**
Star SG 10	SG 10 Star
Okimate 20 (Apple IIe P.M.)	Imagewriter
Toshiba P321**	P321 Toshiba**
Mannesman Spirit 80	Spirit 80 Mann. Tally
Radio Shack DMP 130 (TRS mode)	DMP 130 Tandy
Hewlett-Packard QuietJet+	QuietJet H.P.
Hewlett-Packard QuietJet+***	Wide QuietJet
IBM 5152, Commodore MPS1000 (IBM mode), Epson FX80, Okidata M182a/183a, Okimate 20 (IBM mode), Radio Shack DMP 130 (IBM mode)	ESC-2 Epson/IBM
Citizen MSP 10/15/20/25, Epson LX 80, Star NX-10	Non ESC-2 Epson/IBM
Okidata M1292 (IBM P.M.)*	Oki 29X (IBM)*
Star NB 24-15**	NB-24 Star**
Wide Star NB-24***	Wide NB-24
Okidata M192/193	Oki 19X (Microline)
Star Gemini 10X	Star Gemini 10X
Texas Instruments 857	TI 857
Blue Chip M120/10	M120/10 Blue Chip
Panasonic KX-P1080	KX-P1080 Panasonic

* 16 pin mode (8 pin mode where available)

** 24 pin mode (8 pin mode where available)

*** Use full 15" carriage and printer paper. Printout will exceed one page.

- Select the appropriate printer from the list as shown above table.
- Be sure to "Select Options" also in Printer Setup. This will allow you to set line feeds. If you are unsure what line feeds are please consult your printer/interface manuals. Please ignore the slot number, device number, and the secondary address option as they have no effect on this version.
- "Test Printer" should be done at this time using the 576 x 576 Squareness Test. This should print a 8 x 8 inch square. Only the four corners and the left edge are actually printed to save time.

- If the printout is NOT 8 x 8 inch square then the wrong printer driver was selected.
- If the square has white spaces between lines you may have chosen the wrong printer driver or the line feeds are set wrong.
- After the printer has been setup BE SURE TO "SAVE CHANGES" BEFORE CONTINUING.
- After your printer is setup correctly and you have SAVED THE CHANGES "Exit to AwardWare" and you can start creating awards. See your manual for further instructions. You will NOT have to do Printer Setup again unless you change printers.